

Datenblatt für Artikel: IL900189-A

Plug-in counter bar 50A, PU = 64 Pieces

Smart Meter Terminal 3pole +2N, Test overload current 80A for 1h, Power loss 3,3W at 50A over all three phases, 400VAC, 50Hz, Conductor Material Copper 2,5-16mm², flexible with crimped ferrule, Material Terminal Inserts from Silver-Plated Copper, RoHS konform, OVE R21:2019



SCHRACK-Info

- Meter Connection Terminal 3-pol+2N With TRE 50A, for EVU Czech Republic, Vienna, Tyrol and Styria
- It makes it possible to replace devices without interrupting the power supply
- Power loss 3,3W at 50A over all three phases
- 400VAC, 50Hz
- Material Terminal Inserts from Silver-Plated Copper
- OVE Zertifiziert, RoHS konform, OVE R21:2019
- Ambient Temperature max. 60°C
- Conductor Material/Type Copper 2,5-16mm², rigid, solid and stranded /flexible with crimped ferrule, insertion depth of conductor 18-22mm
- Meter pins IL900190
- Tightening torque of Conductor max. 3Nm
- Material PA6.6

Technische Daten

Nettó szélesség (mm)

149,00

Technische Daten - Fortsetzung

Nettó magasság (mm)	45,00
Nettó mélység (mm)	33,00
Nettó tömeg (kg)	0,11
EAN-CODE	9004840980271
Veszteségi teljesítmény (W)	3,30
Min. környezeti hőmérséklet (°C)	0
Max. környezeti hőmérséklet (°C)	60
Változat	Vienna Styria Tirol
Tartozék	mérőcsatlakozó lécz
Leírás	Kapocs

Artikeltabelle

BEZEICHNUNG	BEST.NR.
Plug-in counter bar 50A, PU = 64 Pieces Smart Meter Terminal 3pole +2N, Test overload current 80A for 1h, Power loss 3,3W at 50A over all three phases, 400VAC, 50Hz, Conductor Material Copper 2,5-16mm ² , flexible with crimped ferrule, Material Terminal Inserts from Silver-Plated Copper, RoHS konform, OVE R21:2019	IL900189-A
Választható tartozék	
Csatlakozó pecsek 6/5 44mm mérőhöz	IL900309
Plug-in counter bar pins 63A, 44mm, PU=7 pieces	IL900190
Cover for Plug-in counter bars	IL900191
for Plug-in counter Terminals IL900189-- The release handle is used to release the springs in the meter terminal, allowing the meter to be inserted or removed. Made of robust IL90029E polyamide.	